



ADC-M65 YZ

SERVICE MANUAL

STEREO CAR
CD CHANGER SYSTEM

BASIC CD MECHANISM : 8ZG-3 RNF

- Replace this Service Manual with "Revision Publishing" when it is issued.

aiwa

S/M Code No. 09-002-404-5T6

SIMPLE

DATA

ELECTRICAL MAIN PARTS LIST - 1 / 3

NOTE: The characters in the suffix column indicate the part usage.

YZ	REF.NO	PARTS NO.	XX. KANRI NO.	DESCRIPTION	A. SUFFIX
C	201	87-010-196-080		CHIP CAPACITOR,0.1-25	
C	202	87-010-196-080		CHIP CAPACITOR,0.1-25	
C	201	87-016-669-080		C-CAP,S 0.1-25 K B	A
C	202	87-016-669-080		C-CAP,S 0.1-25 K B	A
C	221	87-010-498-040		CAP,E 10-16 GAS	
C	222	87-010-552-040		CAP,E 22-16 GAS	
C	251	87-010-197-080		CAP, CHIP 0.01 DM	A
C	251	87-010-497-040		CAP,E 4.7-35 GAS	
C	252	87-012-140-080		CAP 470P	A
D	201	87-A40-196-080		C-ZENER,UDZ6.2B	A
D	251	87-020-331-080		CHIP-DIODE,DAN202K	A
D	254	87-A40-196-080		C-ZENER,UDZ6.2B	A
D	253	87-A40-196-080		C-ZENER,UDZ6.2B	A
D	255	87-A40-196-080		C-ZENER,UDZ6.2B	A
D	252	87-A40-602-040		C-ZENER,UDZ7.5B	
IC	201	8Z-KM3-690-010		C-IC,CXP84632-138Q	
IC	201	8Z-KM3-691-010		C-IC,CXP84632-143Q	A
IC	251	87-A21-158-040		C-IC,TC74HC365AF	A
L	201	87-A50-536-080		C-COIL,10UH K LQH3C24	A
PD	201	87-026-674-010		P-TR,PT4850F	A
PS	201	87-A90-244-010		SNSR,GP1S94	A
Q	201	87-026-648-080		C-TR,UPA608T	A
Q	203	87-A30-272-040		C-TR,DTA124EKA	
Q	202	89-327-125-080		CHIP TR,2SC2712GR	A
Q	222	87-A30-273-040		C-TR,DTC124EKA	
Q	221	87-A30-275-040		C-TR,2SB1123	
Q	252	87-A30-272-040		C-TR,DTA124EKA	A
Q	251	89-327-125-080		CHIP TR,2SC2712GR	A
Q	253	89-327-125-080		CHIP TR,2SC2712GR	A
SW	203	87-036-110-010		PUSH SWITCH	A
SW	202	87-036-110-010		PUSH SWITCH	A
SW	204	87-036-312-080		C-SW,PUSH 102MH4	A
SW	201	87-A91-155-010		SW,TACT SKHHLO	A
X	200	87-A70-200-080		C-VIB,CEER 12MHZ CSTCV12MTJ0C4	A
		8Z-KM1-232-010		HLDR,LED	A
C	107	87-010-184-080		CHIP CAPACITOR 3300P(K)	A
C	107	87-010-186-080		CAP,CHIP 4700P	
C	105	87-010-196-080		CHIP CAPACITOR,0.1-25	
C	104	87-010-196-080		CHIP CAPACITOR,0.1-25	
C	106	87-010-196-080		CHIP CAPACITOR,0.1-25	
C	102	87-010-499-040		CAP,E 22-6.3 GAS	A
C	101	87-010-550-040		CAP,E 100-6.3 GAS	
C	109	87-012-156-080		C-CAP,S 220P-50 CH	A
C	103	87-016-350-040		CAP,E 470-4 MA GAS	
C	108	87-016-526-080		C-CAP,S 0.47-16 BK	A
C	108	87-016-669-080		C-CAP,S 0.1-25 K B	
C	106	87-016-669-080		C-CAP,S 0.1-25 K B	A
C	105	87-016-669-080		C-CAP,S 0.1-25 K B	A
C	104	87-016-669-080		C-CAP,S 0.1-25 K B	A
C	103	87-A12-154-010		CAP,E 470-4 M 7L SRA	A
C	117	87-010-176-080		C-CAP,S 680P-50 SL	A
C	118	87-010-176-080		C-CAP,S 680P-50 SL	A
C	110	87-010-184-080		CHIP CAPACITOR 3300P(K)	A
C	112	87-010-196-080		CHIP CAPACITOR,0.1-25	
C	113	87-010-318-080		C-CAP,S 47P-50 CH	
C	111	87-010-992-080		C-CAP,S 0.047-25 B	A
C	116	87-012-154-080		C-CAP,S 150P-50 CH	A
C	115	87-012-154-080		C-CAP,S 150P-50 CH	A
C	112	87-016-669-080		C-CAP,S 0.1-25 K B	A
C	155	87-010-178-080		CHIP CAP 1000P	
C	159	87-010-318-080		C-CAP,S 47P-50 CH	
C	156	87-010-880-080		C-CAP,E 47-6.3 MF	
C	157	87-010-880-080		C-CAP,E 47-6.3 MF	
C	154	87-010-880-080		C-CAP,E 47-6.3 MF	
C	158	87-010-992-080		C-CAP,S 0.047-25 B	A
C	159	87-012-156-080		C-CAP,S 220P-50 CH	A
C	157	87-012-156-080		C-CAP,S 220P-50 CH	A
C	153	87-016-669-080		C-CAP,S 0.1-25 K B	
C	156	87-016-669-080		C-CAP,S 0.1-25 K B	A
C	152	87-016-669-080		C-CAP,S 0.1-25 K B	A
C	155	87-016-669-080		C-CAP,S 0.1-25 K B	A
C	153	87-A10-711-080		C-CAP,E 100-6.3 M MF	A
C	152	87-A10-711-080		C-CAP,E 100-6.3 M MF	
C	151	87-A10-711-080		C-CAP,E 100-6.3 M MF	A
C	160	87-010-317-080		C-CAP,S 39P-50 CH	
C	161	87-012-156-080		C-CAP,S 220P-50 CH	
C	166	87-016-669-080		C-CAP,S 0.1-25 K B	A
C	161	87-016-669-080		C-CAP,S 0.1-25 K B	A
C	163	87-016-669-080		C-CAP,S 0.1-25 K B	A
C	165	87-016-669-080		C-CAP,S 0.1-25 K B	A
C	162	87-A12-031-080		C-CAP,E 33-10 M MF	A
C	172	87-010-149-080		C-CAP,S 5P-50 CH	
C	171	87-012-156-080		C-CAP,S 220P-50 CH	
C	181	87-016-669-080		C-CAP,S 0.1-25 K B	
C	404	87-010-178-080		CHIP CAP 1000P	
C	403	87-010-196-080		CHIP CAPACITOR,0.1-25	

ELECTRICAL MAIN PARTS LIST - 2 / 3

C	402	87-010-197-080	CAP, CHIP 0.01 DM
C	405	87-010-318-080	C-CAP,S 47P-50 CH
C	401	87-A10-711-080	C-CAP,E 100-6.3 M MF
C	452	87-010-196-080	CHIP CAPACITOR,0.1-25
C	505	87-010-178-080	CHIP CAP 1000P	A.....
C	503	87-010-196-080	CHIP CAPACITOR,0.1-25
C	509	87-010-237-080	CAP, ELECT 1000-16V
C	501	87-010-553-040	CAP,E 47-16 GAS
C	501	87-010-555-040	CAP,E 100-10 GAS	A.....
C	503	87-016-669-080	C-CAP,S 0.1-25 K B	A.....
C	506	87-A11-257-010	CAP,E 470U-10 M UVZ1A	A.....
C	555	87-010-196-080	CHIP CAPACITOR,0.1-25
C	553	87-010-196-080	CHIP CAPACITOR,0.1-25
C	556	87-010-196-080	CHIP CAPACITOR,0.1-25
C	554	87-010-196-080	CHIP CAPACITOR,0.1-25
C	557	87-010-221-080	CAP, ELECT 470-10V
C	551	87-010-552-040	CAP,E 22-16 GAS
C	551	87-010-555-040	CAP,E 100-10 GAS	A.....
C	556	87-016-669-080	C-CAP,S 0.1-25 K B	A.....
C	553	87-016-669-080	C-CAP,S 0.1-25 K B	A.....
C	555	87-016-669-080	C-CAP,S 0.1-25 K B	A.....
C	554	87-016-669-080	C-CAP,S 0.1-25 K B	A.....
C	552	87-A11-257-010	CAP,E 470U-10 M UVZ1A	A.....
C	558	87-A11-257-010	CAP,E 470U-10 M UVZ1A
C	604	87-010-782-010	CAP 0.047F	A.....
C	604	87-A11-258-010	CAP,DL 0.022F-5.5 Z FYDOH
D	151	87-020-330-080	DIODE,DAP202K
D	151	87-A40-250-040	C-DIODE,DAN217	A.....
D	501	87-A40-524-040	C-DIODE,1SR154-400	A.....
IC	101	87-A20-892-010	C-IC,CXD2588R	A.....
IC	151	87-A20-963-040	C-IC,CXA1791N
IC	151	87-A21-467-040	C-IC,CXA2581N	A.....
IC	401	87-A20-574-010	IC,SM5902 AF
IC	451	87-A21-160-040	C-IC,MSM5117400C-60SJ
IC	501	87-A21-161-040	C-IC,BA6392FP	A.....
IC	551	87-A21-162-040	C-IC,BA6247FP	A.....
L	101	87-003-184-080	C-COIL, 10UH K LQH3
L	101	87-A50-536-080	C-COIL,10UH K LQH3C24	A.....
L	151	87-003-184-080	C-COIL, 10UH K LQH3
L	151	87-A50-536-080	C-COIL,10UH K LQH3C24	A.....
L	152	87-A50-536-080	C-COIL,10UH K LQH3C24	A.....
L	401	87-003-184-080	C-COIL, 10UH K LQH3
L	501	87-003-184-080	C-COIL, 10UH K LQH3
L	501	87-A50-536-080	C-COIL,10UH K LQH3C24	A.....
L	551	87-003-184-080	C-COIL, 10UH K LQH3
L	551	87-A50-536-080	C-COIL,10UH K LQH3C24	A.....
Q	152	87-026-608-080	C-TR,DTC 123 JK
Q	151	87-A30-248-040	C-TR,2SB1197KQ	A.....
Q	153	89-110-372-080	TR,2SA1037(140MHZ 200MW)	A.....
Q	151	89-110-372-080	TR,2SA1037(140MHZ 200MW)
R	153	87-022-359-080	C-RES,S22K-1/10WF
R	154	87-022-359-080	C-RES,S22K-1/10WF
X	101	87-A70-163-080	C-VIB,CER 16.93MHZ CSTCVMXJ0C4	A.....
C	605	87-010-196-080	CHIP CAPACITOR,0.1-25
C	601	87-010-552-040	CAP,E 22-16 GAS	A.....
C	603	87-010-552-040	CAP,E 22-16 GAS	A.....
C	608	87-010-805-080	CAP, S 1-16
C	605	87-016-669-080	C-CAP,S 0.1-25 K B	A.....
C	602	87-A10-368-080	C-CAP,S 2.2-10 Z F	A.....
C	606	87-A10-368-080	C-CAP,S 2.2-10 Z F	A.....
C	622	87-010-060-040	CAP,E 100-16
C	623	87-010-060-040	CAP,E 100-16
C	625	87-010-196-080	CHIP CAPACITOR,0.1-25
C	624	87-010-237-080	CAP, ELECT 1000-16V
C	624	87-010-260-080	CAP, ELECT 47-25V	A.....
C	621	87-010-552-040	CAP,E 22-16 GAS	A.....
C	622	87-010-555-040	CAP,E 100-10 GAS	A.....
C	623	87-010-555-040	CAP,E 100-10 GAS	A.....
C	626	87-016-044-040	CAP,E 100-16 GAS	A.....
C	625	87-016-669-080	C-CAP,S 0.1-25 K B	A.....
C	623	87-A10-818-040	CAP,E 100-16 7LSRA SERIES
C	622	87-A10-818-040	CAP,E 100-16 7LSRA SERIES
C	632	87-010-552-040	CAP,E 22-16 GAS	A.....
C	631	87-010-555-040	CAP,E 100-10 GAS	A.....
D	603	87-001-221-080	CHIP DIODEISS319
D	604	87-020-331-080	CHIP-DIODE,DAN202K
D	602	87-070-136-080	ZENER,MTZJ5.1B	A.....
D	602	87-A40-350-080	ZENER,MTZJ 4.7C
D	601	87-A40-524-040	C-DIODE,1SR154-400	A.....
D	624	87-017-931-080	ZENER,MTZJ5.6B
D	622	87-020-331-080	CHIP-DIODE,DAN202K
D	623	87-A40-196-080	C-ZENER,UDZ6.2B
D	624	87-A40-437-080	ZENER,MTZJ4.3B	A.....
D	621	87-A40-524-040	C-DIODE,1SR154-400	A.....
D	631	87-020-331-080	CHIP-DIODE,DAN202K	A.....
D	651	87-020-331-080	CHIP-DIODE,DAN202K	A.....
IC	601	87-A21-102-040	C-IC,S-80828ANNP-EDR-T2	A.....
IC	622	87-A21-190-040	C-IC,PQ20WZ1U	A.....
ICP	601	87-A91-337-080	PROTECTOR,IC ICP-N75	A.....
Q	602	87-A30-272-040	C-TR,DTA124EKA
Q	601	87-A30-274-040	C-TR,2SD1622S-TD	A.....
Q	603	89-327-125-080	CHIP TR,2SC2712GR

ELECTRICAL MAIN PARTS LIST - 3 / 3

C	306	87-015-696-040	CAP,E 2.2-50 SRA	A.....
C	305	87-015-696-040	CAP,E 2.2-50 SRA	A.....
C	322	87-010-196-080	CHIP CAPACITOR,0.1-25
C	324	87-010-196-080	CHIP CAPACITOR,0.1-25
C	325	87-010-550-040	CAP,E 100-6.3 GAS	A.....
C	323	87-010-550-040	CAP,E 100-6.3 GAS	A.....
C	321	87-010-553-040	CAP,E 47-16 GAS	A.....
C	322	87-016-669-080	C-CAP,S 0.1-25 K B	A.....
C	324	87-016-669-080	C-CAP,S 0.1-25 K B	A.....
IC	301	87-017-888-080	IC,NJM4558MD	A.....
L	301	87-003-184-080	C-COIL, 10UH K LQH3
L	301	87-A50-536-080	C-COIL,10UH K LQH3C24	A.....
Q	622	87-A30-273-040	C-TR,DTC124EKA	A.....
Q	621	87-A30-317-080	TR,2SA1702	A.....
Q	623	89-423-952-010	TR,2SD2395E	A.....
Q	631	87-A30-371-040	C-TR,2SD1623	A.....
*		8Z-KM4-606-010	PWB,FLEX DIN (ZKM4)	A.....
*		8Z-KM4-608-010	F-CABLE,2P (SENS KM4)	A.....
*		8Z-KM4-616-010	FF-CABLE, 30P 0.5 80MM	A.....
CN	101	87-A60-918-080	C-CONN,26P SFR26R1ST
CN	101	87-A61-155-080	C-CONN,30P H XF2H-3015-1	A.....
J	901	8Z-KM3-638-010	JACK,DIN 13 P TCS5125-014151	A.....
W	101	8Z-KM4-607-010	FF-CABLE, 26P 0.8 80MM
C	307	87-010-178-080	CHIP CAP 1000P	A.....
C	308	87-010-178-080	CHIP CAP 1000P	A.....
C	303	87-010-318-080	C-CAP,S 47P-50 CH	A.....
C	304	87-010-318-080	C-CAP,S 47P-50 CH	A.....
C	301	87-010-552-040	CAP,E 22-16 GAS	A.....
C	302	87-010-552-040	CAP,E 22-16 GAS	A.....
C	306	87-015-696-040	CAP,E 2.2-50 SRA	A.....
C	305	87-015-696-040	CAP,E 2.2-50 SRA	A.....
C	322	87-010-196-080	CHIP CAPACITOR,0.1-25
C	324	87-010-196-080	CHIP CAPACITOR,0.1-25
C	323	87-010-550-040	CAP,E 100-6.3 GAS	A.....
C	325	87-010-550-040	CAP,E 100-6.3 GAS	A.....
C	321	87-010-553-040	CAP,E 47-16 GAS
C	321	87-010-555-040	CAP,E 100-10 GAS	A.....
C	322	87-016-669-080	C-CAP,S 0.1-25 K B	A.....
C	324	87-016-669-080	C-CAP,S 0.1-25 K B	A.....
C	901	87-010-197-080	CAP, CHIP 0.01 DM	A.....
C	902	87-016-669-080	C-CAP,S 0.1-25 K B	A.....
IC	301	87-017-888-080	IC,NJM4558MD	A.....
L	301	87-003-184-080	C-COIL, 10UH K LQH3
L	301	87-A50-536-080	C-COIL,10UH K LQH3C24	A.....

MECHANICAL PARTS LIST - 1 / 1

NOTE: The characters in the suffix column indicate the part usage.

YZ	REF.NO	PARTS NO.	XX KANRI NO.	DESCRIPTION	A SUFFIX
		8Z-KM1-005-110		WINDOW, CD
		8Z-KM2-002-010		CABI, FRAME 6
		8Z-KM2-003-010		PANEL, FRONT 6	A.....
		8Z-KM2-004-010		WINDOW, FRONT 6	A.....
		8Z-KM2-005-110		CABI, TOP 6
		8Z-KM2-006-010		CABI, BOTTOM 6
		8Z-KM2-008-110		WINDOW, DECK 6
		8Z-KM3-033-010		WINDOW, CD S	A.....
		8Z-KM4-001-010		CABI, FRONT EX66
		8Z-KM4-002-010		CABI, FRONT M60
		8Z-KM4-003-010		CABI, FRONT M65	A.....
		8Z-KM4-004-010		CABI, FRAME 6S	A.....
		8Z-KM4-005-010		WINDOW, DECK M65	A.....
		8Z-KM4-006-010		CABI, TOP 6S	A.....
		8Z-KM4-010-110		WINDOW, DECK M60
		8Z-KM4-013-010		CABI, BOTMOM 6S	A.....
		8Z-KM1-006-110		KEY, EJECT	A.....
		87-571-032-410		VIT+2-3	A.....
		87-B10-244-010		V+2-5 W/O BLK	A.....
		87-B10-245-010		U+2.6-4 W/O CR	A.....
		87-B10-255-010		U+2-3 W/O CR	A.....
		87-B10-260-010		VT+2.6-6 W/O SLOT BLK	A.....
		88-ZG3-355-010		SPR-E, DMPR	A.....
		88-ZG3-371-010		DMPR,	A.....
		8Z-KM1-201-010		HLDR, CD	A.....
		8Z-KM1-202-010		SHAFT, FRAME	A.....
		8Z-KM1-207-010		PLATE, MAG	A.....
		8Z-KM1-220-010		MAGNET, HLDR ASS'Y	A.....
		8Z-KM1-223-010		S-SCREW, 2-5 (BLK)	A.....
		8Z-KM1-225-010		HLDR, REG	A.....
		8Z-KM2-203-010		HLDR, DECK L6	A.....
		8Z-KM2-204-010		HLDR, DECK R6	A.....
		8Z-KM2-205-010		S-SCREW, M3-5-10	A.....
		8Z-KM2-207-010		COVER, PLATE 6	A.....
		8Z-KM2-208-010		COVER, DECK 6	A.....
		8Z-KM2-209-010		S-SCREW, M3-7-7	A.....
		8Z-KM1-232-010		HLDR, LED	A.....
W	101	8Z-KM4-607-010		FF-CABLE, 26P 0.8 80MM

ACCESSORIES / PACKAGE LIST - 1 / 1

NOTE: The characters in the suffix column indicate the part usage.

REF.NO	PARTS NO.	XX KANRI NO.	DESCRIPTION	A SUFFIX
	8Z-KM4-901-010		IB, YU (3L)
	8Z-KM4-904-010		IB, YU (3L) -I
	8Z-KM4-905-010		IB, YZ (9L) -I EXM
	8Z-KM4-906-010		IB, YZ (9L) EXM
	8Z-KM4-907-010		IB, YU (3L) 65 -I
	8Z-KM4-908-010		IB, YZ (9L) 65- I	A.....
	87-B10-208-010		VWWS+4-12 BLK	A.....
	8Z-KM1-210-110		PLATE, UNIT ASSY	A.....
	8Z-KM1-218-010		NUT, 5 HEX-FLANGE	A.....
	8Z-KM2-202-010		HLDR, UNIT 6A	A.....
	8Z-KM2-206-010		HLDR, UNIT 6B	A.....
	8Z-KM4-651-010		CABLE ASSY, 13PIN-DIN	A.....

ELECTRICAL MAIN PARTS LIST - 1 / 1 (8ZG - 3 RNF)

NOTE: The characters in the suffix column indicate the part usage.


REF.NO	PARTS NO.	NO.	DESCRIPTION	SUFFIX
RNF		XX		A
		KANRI		
86-544-437-010		0E	PW, 1.5-3.5-0.5	A
87-261-031-410		0E	V+2-2	A
87-262-545-310		0E	V+2-2.5	A
87-B10-258-010		0E	W-P, 2.15-3.5-0.5	A
88-ZG3-211-110		1H	CHAS ASSY, ELV	A
88-ZG3-221-010		1B	HLDR ASSY, MOT ELV	A
88-ZG3-226-010		1B	LEVER ASSY, SLD-1	A
88-ZG3-231-010		1B	LEVER ASSY, CKG	A
88-ZG3-236-010		1A	ARM ASSY,	A
88-ZG3-246-010		1B	PLATE ASSY, CKG-R	A
88-ZG3-266-110		1A	CLAMP ASSY,	A
88-ZG3-275-010		0E	LEVER, SLD-2	A
88-ZG3-276-310		0E	SPR-P, CLAMP	A
88-ZG3-311-010		0E	GEAR, WORM SLD	A
88-ZG3-312-110		0E	WORM-WHL, SLD	A
88-ZG3-313-010		0E	CAM, SLD	A
88-ZG3-314-010		0E	GUIDE, F	A
88-ZG3-315-210		0E	GUIDE, R	A
8Z-KM1-214-010		1A	HLDR, LED	A
87-067-310-010		0E	PW, 2.1-4-0.15 C	A
87-261-031-410		0E	V+2-2	A
87-262-545-310		0E	V+2-2.5	A
87-571-032-410		0E	VIT+2-3	A
87-B10-272-010			W-P, 2.15-3.5-0.5 SLIT	A
88-ZG3-201-110		2A	CHAS ASSY, MAIN	A
88-ZG3-251-010		1H	CHAS ASSY, TOP	A
88-ZG3-272-110		1B	PLATE, ELV-F	A
88-ZG3-273-110		1B	PLATE, ELV-R	A
88-ZG3-274-010		0E	PLATE, LOCK SW	A
88-ZG3-277-010		0E	SPR-P, MAGAZINE	A
88-ZG3-278-010		0E	PLATE, EJECT	A
88-ZG3-301-010		0E	GEAR, WORM ELV	A
88-ZG3-302-010		0E	WORM-WHL, ELV	A
88-ZG3-303-010		0E	GEAR, ELV	A
88-ZG3-304-010		0E	GEAR, ELV-F	A
88-ZG3-305-010		0E	GEAR, ELV-R	A
88-ZG3-306-210		0E	PLATE, SLIT	A
88-ZG3-331-010		1B	SHAFT, GATA	A
88-ZG3-351-110		0E	SPR-T, LEVER LOCK	A
88-ZG3-352-010		0E	SPR-E, LOCK SW	A
88-ZG3-353-010		0E	SPR-E, EJECT	A
87-067-869-010		0E	V+1.7-8 HL BLK	A
88-ZG3-001-210		1D	MAGAZINE, T	A
88-ZG3-002-210		1C	MAGAZINE, B	A
88-ZG3-003-210		1B	TRAY,	A
88-ZG3-279-210		0E	SPR-P, TRAY	A
87-A91-054-010		1E	MOT, FF-050SK	A
8Z-KM3-623-110		1A	CONN ASSY, 2P (LED)	A
8Z-KM3-625-010		1B	F-CABLE, 4P (SWITCH)	A
CON 803	87-009-863-010	0E	CONN, 2P ZH WHT	A
LED 803	87-A40-319-080	0E	C-LED, LT1E40A GRN	
LED 801	87-A40-319-080	0E	C-LED, LT1E40A GRN	
LED 802	87-A40-320-080	0E	C-LED, LT1H40A Y	
SW 801	87-036-269-080	1A	SW, PUCH ESE102MH1	
SW 802	87-036-312-080	1A	C-SW, PUSH 102MH4	
SW 801	87-036-269-080	1A	SW, PUCH ESE102MH1	A
SW 802	87-036-312-080	1A	C-SW, PUSH 102MH4	A
LED 803	87-A40-319-080	0E	C-LED, LT1E40A GRN	A
LED 801	87-A40-319-080	0E	C-LED, LT1E40A GRN	A
LED 802	87-A40-320-080	0E	C-LED, LT1H40A Y	A

ELECTRICAL MAIN PARTS LIST - 1 / 1 (8ZG - 8 RNF)

NOTE: The characters in the suffix column indicate the part usage.

REF.NO	PARTS NO.	XX KANRI NO.	DESCRIPTION	A SUFFIX
	87-067-800-010		PW 1.5-3.5-0.25SLT	A.....
	87-078-018-010		PW 1.55-3.6-0.25	A.....
	87-262-523-310		V+1.7-2 3 BLK	A.....
	87-262-547-310		V+2-3 BLK	A.....
	87-352-529-310		VT2+1.7-4.0 BLK	A.....
	87-571-032-410		VIT+2-3	A.....
	88-ZG3-256-110		LEVER ASSY, ATK-F	A.....
	88-ZG3-317-010		CLR, ELV	A.....
	88-ZG3-332-010		CLR, LEVER ATK	A.....
	88-ZG3-354-010		SPR-E, LEVER ATK	A.....
	88-ZG8-401-210		CHAS ASSY, MECHA	A.....
	88-ZG8-411-110		SPR-P, LEAD	A.....
	88-ZG8-412-010		SPR-P, PICKUP	A.....
	88-ZG8-421-010		TURN TABLE,	A.....
	88-ZG8-422-010		GEAR, MECHA 1	A.....
	88-ZG8-423-010		GEAR, MECHA 2	A.....
	88-ZG8-424-010		GEAR, MECHA 3	A.....
	88-ZG8-425-010		GUIDE, PICKUP	A.....
	88-ZG8-426-010		HLDR, LEAD	A.....
	88-ZG8-427-010		HLDR, MOT MECHA	A.....
	88-ZG8-428-110		LEVER, PUSH SW	A.....
	88-ZG8-431-010		SHAFT, LEAD	A.....
	88-ZG8-432-010		S-SCREW, V+1.7-5 IB LOCK	A.....
	88-ZG8-433-010		S-SCREW, VIT+2-4 WAX	A.....
	87-A90-926-010		MOT, RF-3LOPA	A.....
	87-A90-927-010		PICKUP, KSS-540A	A.....
	87-A91-054-010		MOT, FF-050SK	A.....
*	8Z-KM3-622-010		PWB, FLEX PICK UP	A.....
*	8Z-KM3-624-010		F-CABLE, 2P (LIMIT)	A.....
*	8Z-KM4-631-010		PWB, FLEX PICK UP (AK)	A.....
PU	0	87-A91-630-010	PICKUP, KSS-710A	A.....
		87-A60-918-080	C-CONN, 26P SFR26R1ST	A.....
		87-A60-919-080	C-CONN, 16P SFR16R1ST	A.....
CON	801	87-A61-155-080	C-CONN, 30P H XF2H-3015-1	A.....
CON	802	87-A61-240-080	C-CONN, 16P H FLZ-RSM1-TB	A.....
SW	803	87-036-312-080	C-SW, PUSH 102MH4	A.....

SCHEMATIC DIAGRAM



H. WAKABATASHI
26/NOV/99
CIRCUIT DIAGRAM

アイワ株式会社 〒110-8710 東京都台東区池之端1-2-11 ☎03(3827)3111 (代表)
AIWA CO.,LTD. 2-11, IKENOHATA 1-CHOME, TAITO-KU, TOKYO 110, JAPAN TEL:03 (3827) 3111